VALUE
VALUE Creates Value

Making Your Job More Enjoyable

VMV-1

Vacuum Gauge

It uses the Pirani high-precision vacuum sensor to precisely measure vacuum levels. Digital display affords a comprehensive view of vacuum conditions. When reaching the preset vacuum level, it will buzz as a reminder. When the vacuum level decreases from the pre-set vacuum level, it will buzz rapidly and flash the backlight to warn of leaks.

Precise Measurement

Ergonomic Design
- Easy to carry

Buzzing Alert
- Vacuum level reminder
- Vacuum leakage warning

Precision Vacuum Sensor
- Pirani sensor

Large Backlit Display
- Easy-to-read large digital display
- Backlit display for clarity

Model	VMV-1
Maximum overload pressure	14 psi / 0.1MPa
Range	0~10000 Pa、0~100.00 mBar、0~75.000 mmHg、0~75000 Microns
Resolution	0.01(< 10 Pa)、0.0001(< 10 mBar)、0.0001(< 10 mmHg)、1(< 30000 Microns)
Accuracy	2~100Pa：±5% of reading(at 20 °C)
Operating temperature	0~50 °C
Unit	Pa、mBar、mmHg、Microns
sensor	Pirani sensor
Dimensions	147x59x33 mm
Weight	Only 125 g